

Appl. No. 10/538,768  
 Amdt. dated October 27, 2006  
 Reply to Office action of September 14, 2006  
 Atty. Docket No. AP1012USN

RECEIVED  
 CENTRAL FAX CENTER

OCT 27 2006

**Amendments to the Claims:**

This listing of claims will replace all prior versions, and listings, of claims in the application:

**Listing of Claims:**

1. (Currently amended) Portable apparatus for measuring parameters of optical signals propagating concurrently in opposite directions in an optical transmission path ~~(16, 16/1, ..., 16/9)~~ between two elements ~~(10, 14/1...14/9)~~ at least one ~~(14/1...14/9)~~ of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2) from the other ~~[[10]]~~ of said elements, the apparatus comprising first and second connector means ~~[[22, 24]]~~ for connecting the apparatus into the optical transmission path in series therewith, and means ~~(32, 38, 46)~~ connected between the first and second connector means for propagating at least said second optical signal (S2) towards said at least one ~~[[14]]~~ of the elements, and measuring said parameters of said concurrently propagating optical signals (S1, S2).

2. (Currently amended) Apparatus according to claim 1, wherein the propagating and measuring means ~~(32, 38, 46)~~ provides an optical signal path between the first and second connector means ~~[[22, 24]]~~ for conveying at least a portion of said second optical signal (S2).

3. (Currently amended) ~~Apparatus according to claim 2, Portable apparatus for measuring parameters of optical signals propagating concurrently in opposite directions in an optical transmission path between two elements), at least one of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2) from the other of said elements, the apparatus comprising first and second connector means for connecting the apparatus into the optical transmission path in series therewith, and means) connected between the first and second connector means for propagating at least said second optical signal (S2) towards said at least one of the elements, and measuring said parameters of said concurrently propagating optical signals (S1, S2).~~

~~wherein the propagating and measuring means (32, 38, 46) provides an optical signal path between the first and second connector means for conveying at least a portion of said second optical signal (S2) and comprises:~~

~~coupler means [[32]] having first and second ports [[28, 30]] connected to the first and second connector means [[22, 24]], respectively, to provide said optical signal path to convey said first (S1) and second (S2) optical signals in opposite directions between said first and second connector means [[22, 24]], and a third port [[34]] for supplying a portion (S1') of said first optical signal (S1),~~

~~detection means (38, 38, 42, 38, 42, 44) for converting at least the first optical signal portion~~

Appl. No. 10/538,768  
Amtd. dated October 27, 2006  
Reply to Office action of September 14, 2006  
Atty. Docket No. AP1012USN

(S1') into a corresponding electrical signal, and

measuring means ~~[[46]]~~ for processing the electrical signal to provide an indication of said measured parameters.

4. (Currently amended) Apparatus according to claim 3, wherein the coupler means ~~[[32]]~~ has a fourth port ~~[[36]]~~ for supplying a portion (S2') of said second optical signal (S2), the detection means ~~(38, 38, 42, 38, 42, 44)~~ also converting at least part of the second optical signal portion (S2') into a corresponding second electrical signal, and the measuring means ~~[[46]]~~ processing both of the electrical signals to provide desired measurement values of parameters for each of the counter-propagating signals.

5. (Currently amended) Apparatus according to claim 1, wherein, where said one of the elements ~~(14/1,..., 14/9)~~ also receives via said optical transmission path a third optical signal (S3) at a different wavelength from that of said second optical signal (S2), the propagating and measuring means ~~[[46]]~~ further comprises means ~~(40, 44, 52, 58, 44, 58, 68)~~ for measuring parameters of the third optical signal (S3).

6. (Currently amended) Apparatus according to claim 4, wherein, where said one of the elements ~~(14/1,..., 14/9)~~ also normally receives via the optical transmission path a third optical signal (S3) at a different wavelength to that of said second optical signal (S2), the propagating and measuring means ~~[[46]]~~ further comprises a splitter ~~[[40]]~~ connected to the coupler means ~~[[32]]~~ for splitting a corresponding optical signal portion (S2', S3') into two parts (S2'', S3''), each comprising portions of both the second and third optical signals, and filter means ~~[[64, 66]]~~ coupled to the splitter ~~[[40]]~~ for separating the two parts according to wavelength before supplying same to said detection means ~~(38, 42, 44)~~.

7. (Currently amended) Apparatus according to claim 4, wherein, where said one of the elements ~~(14/1,..., 14/9)~~ also normally receives via the optical transmission path a third optical signal (S3) at a wavelength different from that of said second optical signal (S2), said propagating and measuring means comprises a wavelength discriminator (68) connected to the coupler ~~[[32]]~~ for separating at least a portion (S2', S3') of the combined second and third optical signals (S2, S3) according to wavelength to obtain corresponding separate portions (S2'', S3'') and supplying same to said detection means ~~(38, 42, 44)~~.

8. (Currently amended) Apparatus according to claim 1, wherein the measuring means comprises a separate detector ~~(38, 42, 44)~~ for each of the measured optical signal portions.

Appl. No. 10/538,768  
 Amdt. dated October 27, 2006  
 Reply to Office action of September 14, 2006  
 Atty. Docket No. AP1012USN

9. (Currently amended) Apparatus according to claim 1, wherein, where one of the optical signals is analog, the measuring means ~~[[46]]~~ is arranged to extract the time-averaged optical power of the signal.

10. (Currently amended) ~~Apparatus according to claim 1; Portable apparatus for measuring parameters of optical signals propagating concurrently in opposite directions in an optical transmission path between two elements, at least one of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2) from the other of said elements, the apparatus comprising first and second connector means for connecting the apparatus into the optical transmission path in series therewith, and means connected between the first and second connector means for propagating at least said second optical signal (S2) towards said at least one of the elements, and measuring said parameters of said concurrently propagating optical signals,~~ wherein, where one (S1) of the optical signals comprises bursts of digital data alternating with hulls, the measuring means ~~[[46]]~~ is arranged to extract the average of the optical power averaged over the duration of the individual bursts.

11. (Currently amended) Apparatus according claim 1, wherein the measuring means ~~[[46]]~~ comprises custom circuitry.

12. (Currently amended) Apparatus according to claim 1, wherein the measuring means ~~[[46]]~~ comprises a suitably-programmed microcomputer.

13. (Currently amended) Apparatus according to claim 1, wherein said measuring means further comprises display means ~~[[60]]~~ for displaying the parameter measurements.

14. (Currently amended) A method of measuring parameters of at least one of optical signals propagating concurrently in opposite directions in an optical transmission path ~~(16, 16/1,..., 19/9)~~ between two elements ~~(10, 14/1...14/9)~~, at least one ~~(14/1...14/9)~~ of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2), the method comprising the steps of:

connecting first and second connector means ~~[[22, 24]]~~ of portable measuring apparatus into the optical transmission path in series therewith,

using the apparatus to propagate at least said second optical signal (S2) towards said at least one ~~[[14]]~~ of the elements, and

measuring said parameters of said at least one of the concurrently propagating optical signals.

15. (Currently amended) A method according to claim 14, wherein the apparatus provides an

Appl. No. 10/538,768  
 Amdt. dated October 27, 2006  
 Reply to Office action of September 14, 2006  
 Atty. Docket No. AP1012USN

optical signal path between the first and second connector means ~~[(22,24)]~~ for at least said second optical signal (S2).

16. (Currently amended) ~~A method according to claim 15, A method of measuring parameters of at least one of optical signals propagating concurrently in opposite directions in an optical transmission path between two elements, at least one of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2), the method comprising the steps of:~~

connecting first and second connector means of portable measuring apparatus into the optical transmission path in series therewith.

using the apparatus to propagate at least said second optical signal (S2) towards said at least one of the elements, and

measuring said parameters of said at least one of the concurrently propagating optical signals, wherein the apparatus has a coupler means ~~[(32)]~~ having first and second ports ~~[(28,30)]~~ connected to the first and second connector means ~~[(22,24)]~~, respectively, to provide said optical signal path for conveying said first (S1) and second (S2) optical signals in opposite directions between said first and second connector means ~~[(22,24)]~~, and a third port ~~[(34)]~~ for a portion (S1') of said first optical signal (S1) propagating in said optical signal path, the apparatus providing an optical signal path between the first and second connector means ~~[(22,24)]~~ for at least said second optical signal (S2),

the method comprising the steps of:

extracting said portion (S1') of said first optical signal (S1) from said third port of the coupler means,

converting the first optical signal portion (S1') into a corresponding first electrical signal, and processing the first electrical signal to provide an indication of said measured parameters.

17. (Currently amended) A method according to claim 16, further comprising the steps of extracting from a fourth port ~~[(36)]~~ of the coupler ~~[(32)]~~ a portion (S2') of said second optical signal (S2) propagating in the optical signal path;

converting the second optical signal portion (S2') into a corresponding second electrical signal; and

processing said first and second electrical signals to provide the desired parameters for each of the counter-propagating optical signals.

18. (Currently amended) A method according to claim 14, wherein, where said one of the elements (14/1,..., 14/9) also receives via the optical transmission path a third optical signal (S3) at a wavelength different from that of said second optical signal (S2), the measuring step also measures

Appl. No. 10/538,768  
Amdt. dated October 27, 2006  
Reply to Office action of September 14, 2006  
Atty. Docket No. AP1012USN

parameters of the third optical signal (S3).

19. (Currently amended) A method according to claim 17, wherein, where said one of the elements ~~(14/1,..., 14/9)~~ also receives via the optical transmission path a third optical signal (S3) co-propagating with the said second optical signal (S2) at a wavelength different from that of the said second optical signal (S2), the measuring step includes the steps of splitting a portion of the co-propagating optical signals into two parts, each comprising portions of the second and third optical signals (S2, S3), separating each of the two parts according to wavelength, converting said parts into said second electrical signal and a third electrical signal, respectively, and also processing the third electrical signal to obtain parameters of the third optical signal (S3).

20. (Currently amended) A method according to claim 17, wherein, where said one of the elements ~~(14/1,..., 14/9)~~ also receives via the optical transmission path a third optical signal (S3) co-propagating with the said second optical signal (S2) at a wavelength different from that of the said second optical signal (S2), said measuring step employs a wavelength discriminator ~~[(68)]~~ connected to the coupler ~~[(32)]~~ for splitting a portion of the co-propagating optical signals into two parts each corresponding to a respective one of the second and third optical signals, converting the parts to said second electrical signal and a third electrical signal, and also processing the third electrical signal to obtain parameters of said third optical signal (S3).

21. (Currently amended) A method according to claim 14, wherein the detection step uses a separate detector ~~(38, 42, 44)~~ for each of the measured optical signals.

22. (Currently amended) A method according to claim 14, wherein, where one of the optical signals is analog, the ~~detection and processing step of measuring said parameters~~ derives the time-averaged optical power of the signal.

23. (Currently amended) ~~A method according to claim 14~~ A method of measuring parameters of at least one of optical signals propagating concurrently in opposite directions in an optical transmission path between two elements, at least one of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2), the method comprising the steps of:

connecting first and second connector means of portable measuring apparatus into the optical transmission path in series therewith,

using the apparatus to propagate at least said second optical signal (S2) towards said at least one of the elements, and

measuring said parameters of said at least one of the concurrently propagating optical signals,

Appl. No. 10/538,768  
Amdt. dated October 27, 2006  
Reply to Office action of September 14, 2006  
Any. Docket No. AP1012USN

wherein, where ~~one (S1) of the optical signals~~ signal whose parameters are measured comprises bursts of digital data alternating with hulls, the ~~detection and processing~~ measuring step derives the average of the optical power of said optical signal averaged over the duration of the individual bursts.

24. (Currently amended) A method according to claim 14, wherein the processing step of measuring said parameters is performed using custom circuitry.

25. (Currently amended) A method according to claim 14, wherein the processing step of measuring said parameters is performed using a suitably-programmed microcomputer.

26. (Previously presented) A method according to claim 14, further comprising the step of displaying the parameter measurements.

27. (Previously presented) A method according to claim 14, wherein the measurements are performed upon optical signals propagating concurrently in opposite directions in an optical transmission path between network elements in a passive optical network.

28. (New) A method of measuring parameters of at least one of optical communications signals propagating concurrently in opposite directions in an optical transmission path between two optical network elements in an optical network, at least one of the optical network elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2), the method comprising the steps of:

connecting first and second connector means of portable measuring apparatus to respective portions of the optical transmission path to connect the apparatus into the optical transmission path in series therewith, the optical network elements being located at respective distal ends of said transmission path portions,

using the apparatus to propagate at least said second optical signal (S2) towards said at least one of the optical network elements, and

measuring said parameters of said at least one of the concurrently propagating optical signals.

29. (New) Portable apparatus for measuring parameters of optical communications signals propagating concurrently in opposite directions in an optical transmission path between two optical network elements at least one of the optical network elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2) from the other of said optical network elements, the apparatus comprising first and second connector means for connecting to respective portions of the transmission path to connect the apparatus into the optical transmission

Appl. No. 10/538,768  
Amdt. dated October 27, 2006  
Reply to Office action of September 14, 2006  
Atty. Docket No. AP1012USN

path in series therewith, the optical network elements being located at respective distal ends of said transmission path portions, and means connected between the first and second connector means for propagating at least said second optical signal (S2) towards said at least one of the optical network elements, and measuring said parameters of said at least one of the concurrently propagating optical signals.